

MODELS

Smart Array 532 Controller

225338-B21

225338-291 (Japan)

- Dual SCSI channels (1 internal/1 external)
- ProLiant™ Integration
- Reliability
- Ultra3 SCSI
- 64-bit Architecture
- 64-bit PCI Bus Design
- Online Capacity Expansion
- Online RAID level Migration

OVERVIEW

The new Smart Array 532 Controller (SA-532) is a 64-bit, 66 MHz dual SCSI channel PCI array controller for entry level hardware-based fault tolerance. Utilizing both SCSI channels (1 internal and 1 external) of the SA-532 allows you to configure up to 28 hard drives to store up to 2TB of storage per PCI slot. The SA-532 provides high reliability and increased performance over the Smart Array 431, thus providing excellent value and lowering the total server ownership cost. In addition, the SA-532 is data compatible with all Wide Ultra3 and Wide Ultra2 drives and servers, offering an unparalleled degree of investment protection. Designed and integrated with Compaq entry-level and workgroup ProLiant servers, this product provides worry-free data protection.

Note: The SA-532 is supported only in 3.3-volt PCI slots of all Ultra2 and Ultra3 servers. The SA-532 is not supported in 5-volt PCI slots.

The SA-532 provides the best performance and capacity for RAID array controllers in entry-level and workgroup Compaq ProLiant servers or in any ProLiant server where hardware RAID is needed at an entry-level price point.

THE SMART ARRAY ADVANTAGE

Compaq's innovative design and integration work of the Smart Array family of products creates customer value that is unmatched in the industry. Use of Smart Array products across multiple applications results in a much lower Total Cost of Ownership (TCO) than any other server storage RAID products. The Compaq Smart Array family brings an unparalleled return on investment through:

- **Data Compatibility** - among all models of Smart Array controllers allows simple and easy upgrades any time needs for higher performance, capacity, and availability increase. Even successive generations of Smart Array controllers understand the data format of other Smart Array Controllers.
- **Consistent Configuration and Management Tools** - all Smart Array products utilize a standard set of management and utility software. These tools minimize Total Cost of Ownership (TCO) by reducing training requirements and technical expertise necessary to install and maintain the Compaq server storage.
- **Universal Hard Drive** - form factor is for use across multiple Compaq servers, disk enclosures and storage systems. With compatibility across many enterprise platforms, you are free to deploy and re-deploy these drives to quickly deliver increased storage capacity, migrate data between systems, and easily manage spare drives.
- **Pre-Failure Warranty** - means Compaq *Insight Manager*™ not only reports when a drive is going to fail but allows replacement of failing drives prior to actual failure. For complete details, consult the Compaq Support Center or refer to your Compaq Server documentation.

COMPAQ

KEY FEATURES

Compatibility with all Ultra2 and Ultra3 LVD family products. In addition, a seamless upgrade to next generation Compaq high performance and high capacity mainstream Ultra3 Smart Array controllers.

Recovery ROM protects against a ROM corruption

Ultra3 SCSI technology delivers high performance and data bandwidth up to 160 MB/s bandwidth per channel

Mix-and-match LVD SCSI compatibility protects your investments and lets you deploy drives as needed

Dual SCSI channels allows for up to 2 TB of storage per server slot

Software consistency among all Smart Array family products: Array Configuration Utility XE (ACU-XE), Array Configuration Utility (ACU), Compaq Insight Manager (CIM), Array Diagnostic Utility (ADU) and SmartStart.

64-bit, 66MHz PCI interface boosts bandwidth up to 533 MB/s total transfer rate

64-bit memory addressing supports servers with greater than 4 GB of memory

3.3 Volt Slot Support Only provides the latest in low-voltage, 64-bit support

32MB Memory optimizes performance and data throughput.

Note: 32 MB of DRAM used for code, transfer buffers, and non-battery backed read cache

Online Management Features: Online Capacity Expansion, Online RAID Level Migration, Online Stripe Size Migration, Online Spares (Global), User Selectable Expand and Rebuild Priority

Pre-Failure Warranty support for hard disk drives (requires Compaq Insight Manager).

Note: Pre-Failure Warranty is available on all Compaq Prosignia and Compaq ProLiant servers using Compaq Insight Manager 2.1 or higher, and covers Pentium® processors, ECC memory and server hard drives (except the 535 MB Fast-SCSI-2 hard drive) using Compaq IDA, IDA-2, Compaq SMART SCSI Array Controllers, Compaq SMART-2 Array Controllers or Compaq Smart Array Controllers. Certain restrictions and exclusions apply. Consult the Compaq Customer Support Center for details.

PRODUCT HIGHLIGHTS

Data Compatibility

Data compatibility among all models of Smart Array Controllers means customers can instantly upgrade their Smart Array products to get to higher performance, capacity and availability. Unlike competitive products, successive generations of Smart Array products understand the data format of other Smart Array controllers, providing investment protection for your Compaq storage solution.

Performance

Compaq's High Performance Architecture sets new boundaries of industry performance expectations!

- Wide Ultra3 SCSI (160 MB/s bandwidth) per channel
- High-performance 64-bit architecture
- 64-bit, 66-MHz PCI bus (533 MB/s bandwidth)

Capacity

Given the rapid growth of user data, the SA-532 is a perfect companion to rapid expansion:

- Dual SCSI channels support up to 28 disk drives
- Up to 2 TB of storage per PCI slot

Availability

Provides increased server uptime by providing advanced storage functionality:

- Online RAID Level Migration (between any RAID level)
- Online Capacity Expansion
- Logical Drive Capacity Extension
- Global Online Spare
- Pre-Failure Warranty

PRODUCT HIGHLIGHTS *(continued)*

Fault Prevention

The following features offer detection of possible failures before they occur, allowing preventive action to be taken:

- S.M.A.R.T.: Self Monitoring Analysis and Reporting Technology first developed at Compaq detects possible hard disk failure before it occurs, allowing replacement of the component before failure occurs.
- Drive Parameter Tracking monitors drive operational parameters, predicting failure and notifying the administrator.
- Dynamic Sector Repairing continually performs background surface scans on the hard disk drives during inactive periods and automatically remaps bad sectors, ensuring data integrity.
- Smart Array Cache Tracking monitors integrity of controller cache, allowing pre-failure preventative maintenance.
- Environment Tracking for External Storage System: Monitors fan speed and cabinet temperature of ProLiant Storage System and newer Compaq storage enclosures.

Fault Tolerance

Keeps data available and server running while a failed drive is being replaced; several fault tolerance configurations are supported including:

- Distributed Data Guarding (RAID 5): This allocates parity data across multiple drives and allows simultaneous write operations. It is recommended for up to 14 hard drives.
- Drive Mirroring (RAID 1, 1+0): This allocates half of the drive array to data and the other half to mirrored data, providing two copies of every file. It is a high-performance RAID.

Fault Recovery

Minimizes downtime, reconstructs data, and facilitates a quick recovery from drive failure

- Recovery ROM: provides a unique redundancy feature that protects from a ROM image corruption. A new version of firmware can be flashed to the ROM while the controller maintains the last known working version of firmware. If the firmware becomes corrupt, the controller will revert back to the previous version of firmware and continue operating. This reduces the risk of flashing firmware to the controller.
- On-Line Spares: Up to two spare drives can be installed prior to drive failure. If a failure occurs, recovery begins with an On-Line Spare and data is reconstructed automatically.

Note: On-Line Spares can only be used with RAID level 1, 1+0, and 5.

Ease of Use

Consistency and Upgradability make the Smart Array family unique in the industry:

- GUI based configuration, management and diagnostic software tools
- Common data formatting between generations of products
- Data migration between servers and external storage enclosures

COMPATIBILITY

Servers

For up to date compatibility, please see the following URL for complete Smart Array 532 compatibility and support information.

<http://www.compaq.com/products/servers/ProLiantstorage/arraycontrollers/comp.html>

Note: Server must have 3.3 volt PCI slot(s) to support the SA-532 Controller.

Operating Systems

- NT® 4.0 Server
- NT 4.0 Enterprise Edition
- NT 4.0 Terminal Server
- Windows® 2000
- Windows 2000 Advanced Server
- NetWare® 4.x
- NetWare 5.x
- Linux® 32
- Linux 64
- AIX-5L (IA-64)
- UnixWare® 7.x
- OpenServer™ 5.x
- Solaris™
- OS/2

Software Suite

All Smart Array products share a common set of configuration, management and diagnostic tools, including Array Configuration Utility XE (ACU-XE), Array Configuration Utility (ACU), Array Diagnostic Utility (ADU), and Insight Manager. This software consistency of tools reduces the cost of training for each successive generation of product and takes much of the guesswork out of troubleshooting field problems. These tools lower the total cost of ownership by reducing training and technical expertise necessary to install and maintain the Compaq server storage.

Compaq Insight Manager

- Powerful server and server options/storage manager tool
- Monitors over 1200 server parameters

Configuration/Diagnostic Utilities

- Compaq Array Configuration Utility XE (ACU-XE)
 - Powerful Web based configuration utility for all Smart Array controllers
 - Provides a graphical view of Compaq drive array configurations
 - Allows for management of multiple arrays over a secure internet connection from anywhere in the world
 - Easy to use Wizards for configuration
 - Runs online on NT v4.0, Windows 2000 and NetWare
- Compaq Array Configuration Utility (ACU)
 - Powerful configuration utility for all Smart Array controllers
 - Provides a graphical view of Compaq drive array configurations
 - Easy to use Wizards for configuration
 - Runs online on NT v4.0, Windows 2000 and NetWare
- Options ROM Configuration for Arrays (ORCA)
 - Rapid configuration during initial install of the OS
- Compaq Array Diagnostic Utility (ADU)
 - Powerful diagnostic utility for all Smart Array controllers

SERVICE & SUPPORT, CAREPAQ™, AND WARRANTY INFORMATION

Software Product Services

- Standalone telephone support
- Rights to new license version
- Media and documentation updates

Hardware Product Services

- Installation services
- On-site maintenance (includes warranty support)
- Response time upgrades during the warranty period
- Post-warranty coverage
- RAID setup and performance consulting via statement of work

For additional hardware installation and maintenance information, please refer to the URLs listed below:

<http://www.compaq.com/services/carepag/us/install/>

<http://www.compaq.com/services/carepag/us/hardware/>

Warranty Upgrade Options

- Response - Upgrade on-site response from next business day to same day 4 hours
- Coverage - Extend hours of coverage from 9 hours x 5 days to 24 hours x 7 days
- Duration - Select duration of coverage for a period of 1, 3, or 5 years

CarePaq Information

Sample part numbers:

- FM-**XHW-36, 3 year, uplift to 5 x 9, Next Day Response
- FM-**4HR-36, 3 year, uplift to 5 x 9, 4-hour Response
- FM-**724-36, 3 year, uplift to 7 x 24, 4-hour Response

** represents a two digit product specific code

- CarePaq is defined as an upgrade to the product warranty attribute, available for a specific duration and hours of coverage.
- CarePaq is not available for less than the product's warranty duration.
- CarePaq is available for sale anytime during the warranty period for most products, but the commencement date will be the same as the Warranty Start Date (delivery date to end user customer). Proof of purchase may be required.
- CarePaq services are prepaid.

For additional CarePaq (hardware & software) information, as well as orderable part numbers, please refer to the URL listed below:

<http://www.compaq.com/services/carepag/index.html>

SPECIFICATIONS

Protocol	Wide Ultra3 SCSI
SCSI Electrical Interface	Low Voltage Differential (LVD)
Drives Supported	Up to 28 Ultra3 and Ultra2 SCSI hard drives <i>Note:</i> The SA-532 will support all Ultra2 and Ultra3 servers, storage enclosures, and hard disk drives. The SA-532 does not support Single Ended hard disk drives, but does support Single Ended tape drives. (Single Ended refers to Wide Ultra SCSI and previous generations of the SCSI protocol).
SCSI Port Connectors	One external and one internal SCSI port
Data Transfer Method	64-Bit PCI bus-master
PCI Bus Speed	64-bit, 66-MHz PCI (533 MB/s maximum bandwidth)
PCI	3.3 volt CPI slot compatibility only <i>Note:</i> The SA-532 is not supported in 5 volt PCI slots.
Simultaneous Drive Transfer Channels	Two
Channel Transfer Rate	320 MB/s total; 160 MB/s per channel
Software upgradeable Firmware	Yes
Cache Memory	32 MB of DRAM used for code, transfer buffers, and non-battery backed read cache
Logical Drives Supported	32
Maximum Capacity	2 TB (28 X 72.8 GB)
Memory Addressing	64-bit, supporting servers memory greater than 4 GB
RAID Support	RAID 5 (Distributed Data Guarding) RAID 1+0 (Striping & Mirroring) RAID 1 (Mirroring) RAID 0 (Striping)
Upgradeable Firmware	1-MB Flashable ROM
Disk Drive and Enclosure Protocol Support	Ultra2 and Ultra3
Dimensions (HxWxD)	15.25 x 11.0 x 4.25 in/38.71 x 27.92 x 10.79 cm
Weight	3.06 lb (1.39 kg)
Warranty	<i>Maximum:</i> The remaining warranty of the Compaq server product in which it is installed (to a maximum three-year limited warranty) <i>Minimum:</i> One-year, on-site limited warranty <i>Pre-Failure Warranty:</i> Drives attached to the Smart Array Controller and monitored under Compaq Insight Manager are supported by a Pre-Failure (replacement) Warranty. For complete details, consult the Compaq Support Center or refer to your Compaq Server Documentation.

OPTIONS

Hard Drives	Wide Ultra3 SCSI Universal Drives – Hot Plug	
	36.4-GB Wide Ultra3 SCSI 15,000 rpm Drive (1")	232916-B22
	18.2-GB Wide Ultra3 SCSI 15,000 rpm Drive (1")	188122-B22
	9.1-GB Wide Ultra3 SCSI 15,000 rpm Drive (1")	188120-B22
	72.8-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	232432-B22
	36.4-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	176496-B22
	18.2-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	142673-B22
	9.1-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	142671-B22
	36-GB Wide Ultra3 SCSI 10,000 rpm Drives (1"), 10 pack	232617-B21
	18-GB Wide Ultra3 SCSI 10,000 rpm Drives (1"), 10 pack	202352-B21
	Wide Ultra3 SCSI Drives – Non-Hot Plug	
	36.4-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	176497-B21
	18.2-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	142674-B21
	9.1-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	142672-B21

Note: **This is a list of supported hard disk drives** (note that some drives may be discontinued).

OPTIONS (continued)

Software	SANWorks Virtual Replicator	
	Note: For additional Virtual Replicator ordering information refer to http://www.compaq.com/products/StorageWorks/swvr/swvrorderinfo.html	
	License & Media (CD-ROM)	191802-B21
Universal Hot Plug Tape Drives	AIT 50 GB, Hot Plug (Carbon)	215487-B21
	AIT 35 GB, LVD Hot Plug (Carbon)	216886-B21
	20/40-GB DAT, Hot Plug (Carbon)	215488-B21
Storage Enclosures	Compaq <i>StorageWorks</i> Enclosure Model 4314T	190210-001
	Compaq StorageWorks Enclosure Model 4314T (Int'l)	190210-B31
	Compaq StorageWorks Enclosure Model 4314T (Japan)	190210-291
	Compaq StorageWorks Enclosure Model 4314R	190209-001
	Compaq StorageWorks Enclosure Model 4314R (Int'l)	190209-B31
	Compaq StorageWorks Enclosure Model 4314R (Japan)	190209-291
	Compaq StorageWorks Enclosure Model 4354R	190211-001
	Compaq StorageWorks Enclosure Model 4354R (Int'l)	190211-B31
	Compaq StorageWorks Enclosure Model 4354R (Japan)	190211-291
Related Products	Compaq RAID LC2 Controller	188044-B21
	Compaq RAID LC2 Controller (Japan)	188044-291
	Compaq Smart Array 5302/32 Controller	166207-B21
	Compaq Smart Array 5302/32 Controller (Japan)	166207-291
	Compaq Smart Array 5302/64 Controller	124992-B21
	Compaq Smart Array 5302/64 Controller (Japan)	124992-291
	Compaq Smart Array 5304/128 Controller	158939-B21
	Compaq Smart Array 5304/128 Controller (Japan)	158939-291
	Compaq Smart Array 5302/128 Controller	283552-B21
	Compaq Smart Array 5302/128 Controller (Japan)	283552-291
	Compaq Smart Array 5304/256 Controller	283551-B21
	Compaq Smart Array 5304/256 Controller (Japan)	283551-291

© 2002 Compaq Information Technologies Group, LP.

Compaq, the Compaq logo, CarePac, Compaq Insight Manager and ProLiant are trademarks of Compaq Information Technologies Group, L.P. in the U.S. and/or other countries. Windows NT is a registered trademark or trademark of Microsoft Corporation in the U.S. and/or other countries. Pentium is a registered trademark or trademark of Intel Corporation in the U.S. and/or other countries. Linux is a registered trademark or trademark of Linus Torvalds in the U.S. and/or other countries. NetWare is a registered trademark or trademark of Novell Inc., in the U.S. and/or other countries. Solaris is a registered trademark or trademark of Sun Microsystems, Inc., in the U.S. and/or other countries. OpenServer is a registered trademark or trademark of Caldera International, Inc., in the U.S. and/or other countries. UNIX and UnixWare are registered trademarks or trademarks of The Open Group in the U.S. and/or other countries. All other product names mentioned herein may be trademarks of their respective companies.

Compaq shall not be liable for technical or editorial errors or omissions contained herein. The information is provided "as is" without warranty of any kind and is subject to change without notice. The warranties for Compaq products are set forth in the express limited warranty statements accompanying such products. Nothing herein should be construed as constituting an additional warranty.